

GERMAN
POOL

UNIVERSAL TRAVEL ADAPTOR

UTA-PD65W



USER MANUAL

Please read these instructions and warranty information carefully before use and keep them handy for future reference.

Warnings and Safety Precautions

1. Always disconnect this product from the outlet when not in use.
2. Before use, please read this instruction carefully! This product does not convert voltage (AC-AC), in order to avoid possible damage to your device or other safety hazards, please make sure the power outlet you intend to use has the proper voltage to run your device before using this adaptor.
4. This product is for Indoor use only.
5. Misuse of this product can lead to electrical shock.
6. When using this product, the length of the USB cable should be less than 3m.
7. This travel adaptor is for temporary use only and that it shall not be used permanently.
8. The manufacturer prohibits inserting an adaptor into another adaptor.
9. No grounding. This product is for use with unearthed or double insulated appliances only.




Waste electrical products should not be disposed of with household waste. Please recycle where facilities exist. Check with your Local Authority for recycling advice.

Warranty Terms & Conditions

1. Customer who fails to present original purchase invoice will not be eligible for free warranty service.
2. Customer should always follow the operating instructions. This warranty does not apply to: Damages caused by accidents of any kind (including material transfer and others); Operating failures resulting from applying incorrect voltage, improper usage, and unauthorized installations or repairs.
3. This warranty is invalid if: the purchase invoice is modified by an unauthorized party; the product is used for any commercial or industrial purposes; the product is repaired or modified by unauthorized personnel, or unauthorized parts are installed; the serial number is modified, damaged or removed from the product.
4. German Pool will, at its discretion, repair or replace any defective part.
5. This warranty will be void if there is any transfer of ownership from the original purchaser.

Product Structure




- | | |
|------------------------|----------------|
| 1. Multi-socket | 5. USB-A2 Port |
| 2. USA/JP socket | 6. USB-A1 Port |
| 3. USA/AU/UK/EU Plugs | 7. USB-C2 Port |
| 4. LED Indicator Light | 8. USB-C1 Port |

Note:

When in use, LED indicator lights up constant means product is operating normally; if LED indicator light goes dark during use, it means product may be overloaded. Unplug one device and check indicator light status again.

Changing The Fuse




1. Remove the protective cover and take out the spare fuse from location 2.
2. Take out the blown fuse from location 1, place in the new fuse, and push it back into its slot. The product is now ready for use again.
3. You can purchase spare fuse to put inside location 2 (standard: 250V, 10A, 6.3*25.4mm).

Note:

1. Remove all devices before changing the fuse.
2. Check if there is any water coming out of the product. Make sure the fuse is not blown due to the product short-circuiting.
3. Make sure the fuse is not blown due to the product being damp.

Applicable Outlets


This product can accept Type A / B / C / E / F / G / I / J / L / N plugs.



Note:

This product does not accept type D / H / O plugs.

This product can plug into Type A / B / C / D / E / F / G / H / I / J / K / L / N / O outlets.



EU Plug Compatible Countries & Regions (for reference only)

Albania, Algeria, Angola, Argentina, Austria, Azores, Balearic Islands, Bangladesh, Belgium, Bolivia, Bosnia, Brazil, Bulgaria, Burkina Faso, Burundi, Cameroon, Canary Island, Cape Verde, Central African Republic, Channel Islands, Chile, Comoros, Congo, Croatia, Cote d'Ivoire, Cyprus, Denmark, Djibouti, Egypt, El Salvador, Equatorial Guinea, Eritrea, Faeroe Islands, Finland, France, Gabon, Germany, Gibraltar, Greece, Greenland, Guadeloupe, Guinea, Guinea-Bissau, Hungary, Iceland, India, Indonesia, Iran, Iraq, Israel, Italy, Kazakhstan, Korea, Kuwait, Laos, Lebanon, Lithuania, Luxembourg, Macedonia, Madagascar, Madeira, Mali, Martinique, Mauritius, Monaco, Morocco, Mozambique, Myanmar, Nepal, Netherlands, Niger, Norway, Oman, Pakistan, Paraguay, Peru, Philippines, Poland, Portugal, Romania, Russia, Rwanda, Senegal, Somalia, Spain, Sudan, Suriname, Sweden, Switzerland, Syria, Thailand, Togo, Tunisia, Turkey, Uruguay, Vietnam, Zambia.

AUS Plug Compatible Countries & Regions (for reference only)

American Samoa, Argentina, Australia, China, El Salvador, Fiji, Guatemala, Kiribati, Nauru, New Zealand, Panama, Papua New Guinea, St. Vincent, Tajikistan, Tonga, Uruguay.

USA Plug Compatible Countries & Regions (for reference only)

American Samoa, Anguilla, Antilles, Aruba, Bahamas, Bangladesh, Barbados, Bermuda, Bolivia, Brazil, Cambodia, Canada, Cayman Islands, China, Colombia, Costa Rica, Cuba, Ecuador, El Salvador, Guam, Guatemala, Guyana, Haiti, Honduras, Japan, Jamaica, Laos, Lebanon, Liberia, Maldives, Mexico, Micronesia, Montserrat, Netherlands, Nicaragua, Niger, Okinawa, Panama, Peru, Philippines, Puerto Rico, St. Vincent, Saudi Arabia, Tahiti, Taiwan, Thailand, United States, Venezuela, Vietnam, Virgin Islands (US & British), Yemen.

UK Plug Compatible Countries & Regions (for reference only)

Bahrain, Bangladesh, Belize, Botswana, Brunei, Cameroon, Channel Islands, Cyprus, Dominica, El Salvador, Gambia, Ghana, Gibraltar, Grenada, Guatemala, Guyana, Iraq, Ireland, Isle of Man, Jordan, Kuwait, Lebanon, Macau, Malawi, Malaysia, Maldives, Malta, Mauritius, Myanmar, Nigeria, Oman, Qatar, St. Lucia, St. Vincent, Saudi Arabia, Seychelles, Sierra Leone, Singapore, Tanzania, Uganda, United Arab Emirates, United Kingdom, Vietnam, Yemen, Zambia, Zimbabwe.

How To Use

2-Pole Unearthed Devices

This product is suitable for use with most electronic devices up to 2,500W at 250V, and 1,000W at 100V. It can be used with a multitude of appliances such as: laptops, small travel hairdryers, travel irons, electric fans, table lamps, electric razors, etc.

Please check the safety data sheet or data plate on the device to find this information before plugging it in.

USB Devices

This product is suitable for use with most cameras, smartphones, tablets, portable game consoles, Bluetooth speakers, power banks, etc.

How To Use This Product

This product is built-in with multi-nation plugs to fit all outlets in different countries. Safety function switch ensures only one plug is energized.

Note:

1. When pushing down and sliding the button to protract or retract the plug, make sure the plug has protracted or retracted completely, and the button has snapped up and locked in place. **If** the button is not locked, it means the plug has not been completely protracted or retracted, and will affect its normal use.
2. Only one plug type can be used at one time, when one type is protracted, the other plug-pins are locked automatically.



Using USA Plug

To Use: Press “USA/AUS” button and slide out the pins completely and the button is locked in place. Note that the two pins should be parallel to each other (see diagram).

After Use: Press “USA/AUS” button and retract the pins until the button is locked in place.



Using AUS Plug

To Use: Press “USA/AUS” button and slide out the pins completely and the button is locked in place. Turn the two pins inward until they form a “/ \” shape (see diagram).


After Use: Press “USA/AUS” button and retract the pins until the button is locked in place.



Using UK Plug

To Use: Press “UK” button and slide out the pins completely and the button is locked in place. (see diagram).

After Use: Press “UK” button and retract the pins until the button is locked in place.



Using EU Plug

To Use: Press “EU” button and slide out the pins completely and the button is locked in place. (see diagram).

After Use: Press “EU” button and retract the pins until the button is locked in place.

Technical Specification

Model	UTA-PD65W
AC Input	100-250V~, 50/60Hz 10A Max, 2500W Max
DC Output	65W
Fuse	10A
Material	Flame Retardant PC
Product Dimensions	(H)69 (W)54.5 (D)55.5 mm

- Rating: 100-250V ~ / 10A Max/ 2,500W Max
- Input: 100-250V~ / 50-60Hz / 1.6A
- Single Port Output Mode:
USB-C1: 5.0V~3.0A 15.0W, 9.0V~3.0A 27.0W, 12.0V~3.0A 36.0W, 15.0V~3.0A 45.0W, 20.0V~3.25A 65.0W / USB-C2: 5.0V~3.0A 15.0W, 9.0V~3.0A 27.0W, 12.0V~3.0A 36.0W, 15.0V~3.0A 45.0W, 20.0V~3.0A 60.0W / USB-A1: 5.0V~3.0A 15.0W, 9.0V~3.0A 27.0W, 10.0V~2.25A 22.5W, 12.0V~3.0A 36.0W, 20.0V~3.0A 60.0W
USB-A2: 5.0V~1.0A 5.0W
- Multi-Port Output Mode:
C1+C2/A1: 40.0W+18.0W / C1+A2: 60.0W+5.0W / C2+A1: 15.0W / C2+A1+A2: 15.0W (C2+A1) + 5.0W / C1+C2/A1+A2: 40.0W+18.0W+5.0W / C1+C2+A1+A2: 40.0W+15.0W (C2+A1) + 5.0W
- Total DC Output: 65.0W
- Support PD3.0, QC4+, FCP, SCP, AFC, PPS, BC1.2 and more
- Working Temperature Range: 0°C - 40°C

Note:

Does not convert voltage.



- Specification is subject to change without prior notice.
- If there is any inconsistency or ambiguity between the English version and the Chinese version, the Chinese version shall prevail.
- Refer to www.germanpool.com for the most update version of the user manual.

保用條款

此保用提供德國寶產品之機件在正常使用下壹年保用(自購買日起計算)。

貴戶須在購機十天內，以下列其中一種方式登記資料，保用手續方正式生效：

- 1) 填妥德國寶VIP手機應用程式
保用登記表(掃描右方二維碼)
- 2) 填妥本公司網頁保用登記表
www.germanpool.com/warranty
- 1) Visit our VIP App and register online:
(Scan the QR Code on the right)
- 2) Visit our website and register online:
www.germanpool.com/warranty

Warranty Terms & Conditions

Under normal operations, the product will guarantee a 1-year full warranty provided by German Pool (effective from the date of purchase).

This warranty is not valid until customer registration information is received by our Service Centre within 10 days of purchase via one of the following means:



另請填妥以下表格並與正本發票一併保存，以便維修時核對資料。用戶提供之所有資料必須正確無誤，否則免費保用將會無效。

Please fill out the form below. This information and the original purchase invoice will be required for any repairs. Warranty will be invalidated if information provided is found to be inaccurate.

型號 Model No.: UTA-PD65W

發票號碼 Invoice No.: _____

機身號碼 Serial No.: _____

購買商號 Purchased From: _____

購買日期 Purchased Date: _____

此保用只適用於香港及澳門

This warranty is valid only in Hong Kong and Macau

警告及注意事項

1. 不使用本產品時，必須從插座拔下本產品。
2. 使用前必須先仔細閱讀本說明書。本產品不進行電壓轉換（AC-AC），為避免可能損壞您的設備或其他安全隱患，必須在使用本產品前，確保您要使用的電源插座具有足夠的電壓來運作您的裝置。
4. 本產品僅限室內使用。
5. 誤用本產品可能導致觸電。
6. 使用本產品時，適用的USB線長度應小於3米。
7. 本產品僅供臨時使用，嚴禁永久使用。
8. 製造商規定禁止將一個適配器插入另一個適配器中使用。
9. 不接地，本產品僅適用於不接地或雙重絕緣的電器。




本產品不能與生活廢品一起棄置。本產品應棄置在官方回收電子電氣產品的地方。通過收集回收垃圾，會對節省自然資源有幫助。請確保本產品通過對環境友好健康的方式進行報廢。

保用條款

1. 未能出示購買發票正本者，將不獲免費維修服務。
2. 用戶應依照說明書的指示操作。本保用並不包括：
因天然與人為意外造成的損壞（包括運輸及其他）；
電源接合不當、不依說明書而錯誤或疏忽使用本機所引致之損壞。
3. 於下列情況下，用戶之保用資格將被取消：
購買發票有任何非認可之刪改；產品被用作商業或工業用途；產品經非認可之技術人員改裝或加裝任何配件；機身編號被擅自塗改、破壞或刪除。
4. 總代理有權選擇維修或更換配件或其損壞部份。
5. 產品一經被轉讓，其保用即被視作無效。

產品結構




- | | |
|------------------|-------------|
| 1. 萬能插座 | 5. USB-A2接口 |
| 2. 美國/日本插座 | 6. USB-A1接口 |
| 3. 美國/澳洲/英國/歐盟插頭 | 7. USB-C2接口 |
| 4. LED指示燈 | 8. USB-C1接口 |

注意：

使用時LED指示燈常亮代表產品正常操作；如使用時LED指示燈熄滅，代表產品可能超負荷，請嘗試拔除一個設備的插頭，再檢查LED指示燈是否亮著。

更換保險絲




1. 打開位置2的軟膠蓋，取出備用保險絲。
2. 從位置1取出舊有保險絲，置入新的保險絲，並將保險絲槽推回原位；完成後產品可正常使用。
3. 您亦可自行購買適用的保險絲（標準為：250V，10A；尺寸為6.3*25.4mm）

注意：

1. 更換保險絲前必須拔除所有設備插頭。
2. 請確認是否因有水流入本產品內部而導致短路燒毀保險絲。
3. 請確認是否因本產品受潮而燒毀保險絲。

適用範圍


本產品適用於A、B、C、E、F、G、I、J、L及N型插頭。



注意：

本產品不適用於D、H及O型插頭。

本產品適用於A、B、C、D、E、F、G、H、I、J、K、N及O型插座。



歐盟插頭適用國家及地區（僅供參考）

阿爾巴尼亞、阿爾及利亞、安哥拉、阿根廷、奧地利、亞速爾群島、巴利阿里群島、孟加拉、比利時、玻利維亞、波斯尼亞、巴西、保加利亞、布基納法索、布隆迪、喀麥隆、加那利群島、維德角、中非共和國、英吉利海島、智利、科摩羅、剛果、克羅地亞、科特迪瓦、塞浦路斯、丹麥、吉布提、埃及、薩爾瓦多、赤道幾內亞、厄立特里亞、法羅群島、芬蘭、法國、加蓬、德國、直布羅陀、希臘、格陵蘭、瓜德羅普、幾內亞、幾內亞比紹、匈牙利、冰島、印度、印尼、伊朗、伊拉克、以色列、義大利、哈薩克斯坦、韓國、科威特、寮國、黎巴嫩、立陶宛、盧森堡、馬其頓、馬達加斯加、馬德拉、馬利、馬提尼克、茅利塔尼亞、毛里求斯、摩納哥、摩洛哥、莫三比克、緬甸、尼泊爾、荷蘭、尼日爾、挪威、阿曼、巴基斯坦、巴拉圭、秘魯、菲律賓、波蘭、葡萄牙、羅馬尼亞、俄羅斯、盧旺達、塞內加爾、索馬利亞、西班牙、蘇丹、蘇里南、瑞典、瑞士、敘利亞、泰國、多哥、突尼斯、土耳其、烏拉圭、越南、贊比亞。

澳洲插頭適用國家及地區（僅供參考）

美屬薩摩亞、阿根廷、澳洲、中國、薩爾瓦多、斐濟、危地馬拉、基里巴斯、瑙魯、紐西蘭、巴拿馬、巴布亞新幾內亞、聖文森特、塔吉克斯坦、湯加、烏拉圭。

美國插頭適用國家及地區（僅供參考）

美屬薩摩亞、安圭拉、安的列斯、阿魯巴、巴哈馬、孟加拉、巴巴多斯、百慕達、玻利維亞、巴西、柬埔寨、加拿大、開曼群島、中國、哥倫比亞、哥斯達黎加、古巴、厄瓜多爾、薩爾瓦多、關島、危地馬拉、圭亞那、海地、洪都拉斯、日本、牙買加、寮國、黎巴嫩、賴比瑞亞、馬爾代夫、墨西哥、密克羅尼西亞、蒙特塞拉特、荷蘭、尼加拉瓜、尼日爾、沖繩、巴拿馬、秘魯、菲律賓、波多黎各、聖文森特、沙特阿拉伯、大溪地、台灣、泰國、美國、委內瑞拉、越南、維京群島（美屬及英屬）、葉門

英國插頭適用國家及地區（僅供參考）

巴林、孟加拉、貝里斯、博茨瓦納、汶萊、喀麥隆、海峽群島、塞浦路斯、多米尼克、薩爾瓦多、岡比亞、加納、直布羅陀、格林納達、危地馬拉、圭亞那、伊拉克、愛爾蘭、曼島、約旦、科威特、黎巴嫩、澳門、馬拉威、馬來西亞、馬爾代夫、馬耳他、毛里裘斯、緬甸、尼日利亞、阿曼、卡塔爾、聖露西亞、聖文森特、沙特阿拉伯、塞舌爾、塞拉利昂、新加坡、坦桑尼亞、烏干達、阿拉伯聯合酋長國、英國、越南、葉門、贊比亞、津巴布韋。

使用本產品

使用兩腳非接地設備

本產品適用於大多數電子設備，當電壓使用250V時功率可達2,500W，當電壓使用100V時功率可達1,000W。本產品可與多種電器搭配使用，例如筆記型電腦、小型旅行風筒、旅行熨斗、電風扇、檯燈、電動剃鬚刀等。

在插入設備使用之前，必須先檢查該設備上的安全資料表或規格銘牌以查找此資訊。

使用USB插頭

本產品適用於相機、智能手機、平板電腦、手提遊戲機、藍牙耳機、行動電源等。

如何使用本產品

本產品內建多國插頭，適用於不同國家的插座。配備安全功能開關，確保只有一個插頭通電。

注意：

- 滑動按鈕推出插頭或收回插頭時，必須確保按鈕徹底推出或收回，直至按鈕呈彈出狀態。如按鈕未有彈出，表示未推到位，將影響正常使用。
- 每次只能使用一種插頭類型，當推出其中一個插頭時，其他插頭接腳自動鎖定。



使用美國插座

使用時：輕按「USA/AUS」按鈕並向外滑動，直至插頭完全推出及按鈕彈出，注意插腳應為完全垂直（如圖）。

使用完畢：輕按「USA/AUS」按鈕向內收回，直至插頭完全收回及按鈕彈出然後放開按鈕以鎖定插頭。



使用澳洲插座

使用時：輕按「USA/AUS」按鈕並向外滑動，直至插頭完全推出及按鈕彈出，將插腳向外翻成「A」字型（如圖）。

使用完畢：輕按「USA/AUS」按鈕向內收回，直至插頭完全收回及按鈕彈出然後放開按鈕以鎖定插頭。



使用英國插座

使用時：輕按「UK」按鈕並向外滑動，直至插頭完全推出及按鈕彈出（如圖）。

使用完畢：輕按「UK」按鈕向內收回，直至插頭完全收回及按鈕彈出然後放開按鈕以鎖定插頭。



使用歐盟插座

使用時：輕按「EU」按鈕並向外滑動，直至插頭完全推出及按鈕彈出（如圖）。

使用完畢：輕按「EU」按鈕向內收回，直至插頭完全收回及按鈕彈出然後放開按鈕以鎖定插頭。

技術規格

型號	UTA-PD65W
交流電輸入	100-250V~,50/60Hz 10A Max, 2500W Max
直流電輸出	65W
保險絲	10A
物料	PC防火物料
產品尺寸	(H)69 (W)54.5 (D)55.5 mm

- 電壓/電流/功率：100-250V ~ / 10A Max/ 2,500W Max
- 輸入電壓/頻率/電流：100-250V~ / 50-60Hz / 1.6A
- 單埠輸出模式：
USB-C1: 5.0V-3.0A 15.0W, 9.0V-3.0A 27.0W, 12.0V-3.0A 36.0W, 15.0V-3.0A 45.0W, 20.0V-3.25A 65.0W / USB-C2: 5.0V-3.0A 15.0W, 9.0V-3.0A 27.0W, 12.0V-3.0A 36.0W, 15.0V-3.0A 45.0W, 20.0V-3.0A 60.0W / USB-A1: 5.0V-3.0A 15.0W, 9.0V-3.0A 27.0W, 10.0V-2.25A 22.5W, 12.0V-3.0A 36.0W, 20.0V-3.0A 60.0W
USB-A2: 5.0V-1.0A 5.0W
- 多埠輸出模式：
C1+C2/A1: 40.0W+18.0W / C1+A2: 60.0W+5.0W / C2+A1: 15.0W / C2+A1+A2: 15.0W (C2+A1) + 5.0W / C1+C2/A1+A2: 40.0W+18.0W+5.0W / C1+C2+A1+A2: 40.0W+15.0W (C2+A1) + 5.0W
- 總直流輸出：65.0W
- 支援PD3.0, QC4+, FCP, SCP, AFC, PPS, BC1.2等
- 操作溫度範圍：0°C -40°C

注意：
不支援電壓轉換。



- 產品規格及設計如有變更，恕不另行通知。
- 中英文版本如有出入，一概以中文版為準。
- 本產品使用說明書以www.germanpool.com網上版為最新版本。